

### Is Now Part of



# ON Semiconductor®

To learn more about ON Semiconductor, please visit our website at <a href="https://www.onsemi.com">www.onsemi.com</a>

ON Semiconductor and the ON Semiconductor logo are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any EDA Class 3 medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officers, employees, emplo



July 2010


# FJD5304D High Voltage Fast Switching Transistor

#### **Features**

- · Built-in Free Wheeling Diode
- · Wide Safe Operating Area
- · Small Variance in Storage Time
- · Suitable for Electronic Ballast Application



1. Base 2. Collector 3. Emitter



# **Absolute Maximum Ratings** $T_a = 25$ °C unless otherwise noted

Symbol	Parameter	meter Value	
V <sub>CBO</sub>	Collector-Base Voltage	700	V
V <sub>CEO</sub>	Collector-Emitter Voltage	400	V
V <sub>EBO</sub>	Emitter-Base Voltage	12	V
I <sub>C</sub>	Collector Current (DC)	4	Α
I <sub>CP</sub>	* Collector Current (Pulse)	8	Α
I <sub>B</sub>	Base Current (DC)	2	Α
I <sub>BP</sub>	* Base Current (Pulse)	4	А
P <sub>C</sub>	Collector Dissipation $T_c = 25^{\circ}C$ $T_a = 25^{\circ}C$	30 1.25	W W
T <sub>J</sub>	Junction Temperature	150	°C
T <sub>STG</sub>	Storage Temperature	-55 to 150	°C

<sup>\*</sup> Pulse Test: PW = 300µs, Duty Cycle = 2% Pulsed

# **Thermal Characteristics** $T_a = 25^{\circ}C$ unless otherwise noted

Symbol	Parameter	Value	Units
$R_{\theta ja}$	Thermal Resistance Junction-Ambient **	99	°C/W

<sup>\*\*</sup> Device mounted on minimum pad size.

### **Package Marking and Ordering Information**

Device Marking	Device	Package	Reel Size	Tape Width	Quantity
J5304D	FJD5304DTM	D-PAK	13" Dia	-	2500
J5304D	FJD5304DTF	D-PAK	13" Dia	-	2000

# **Electrical Characteristics** $T_a = 25^{\circ}C$ unless otherwise noted

Symbol	Parameter	Conditions	Min.	Тур.	Max.	Units
BV <sub>CBO</sub>	Collector-Base Breakdown Voltage	I <sub>C</sub> = 1mA, I <sub>E</sub> = 0	700			V
BV <sub>CEO</sub>	Collector-Emitter Breakdown Voltage	$I_C = 5mA$ , $I_B = 0$	400			V
BV <sub>EBO</sub>	Emitter-Base Breakdown Voltage	$I_E = 1 \text{mA}, I_C = 0$	12			V
I <sub>CES</sub>	Collector Cut-off Current	V <sub>CB</sub> = 700V, I <sub>E</sub> = 0			100	μΑ
I <sub>CEO</sub>	Collector Cut-off Current	V <sub>CB</sub> = 400V, I <sub>B</sub> = 0			250	μΑ
I <sub>EBO</sub>	Emitter Cut-off Current	V <sub>EB</sub> = 12V, I <sub>C</sub> = 0			1	mA
h <sub>FE</sub>	DC Current Gain	$V_{CE} = 5V, I_{C} = 10mA$ $V_{CE} = 5V, I_{C} = 2.0A$	10 8		40	
V <sub>CE(sat)</sub>	Collector-Emitter Saturation Voltage	$I_C = 0.5A, I_B = 0.1A$			0.7	V
		I <sub>C</sub> = 1.0A, I <sub>B</sub> = 0.2A			1.0	V
		$I_C = 2.5A, I_B = 0.5A$			1.5	V
V <sub>BE(sat)</sub>	Base-Emitter Saturation Voltage	$I_C = 0.5A, I_B = 0.1A$			1.1	V
		I <sub>C</sub> = 1.0A, I <sub>B</sub> = 0.2A			1.2	V
		$I_C = 2.5A, I_B = 0.5A$			1.3	V
t <sub>STG</sub>	Storage Time	V <sub>CLAMP</sub> =200V, I <sub>C</sub> =2.0A,		0.6		μS
t <sub>F</sub>	Fall Time	$I_{B1}$ =0.4A, $V_{BE}$ (off)=-5V, L=200 $\mu$ H		0.1		μS
t <sub>STG</sub>	Storage Time	V <sub>CC</sub> =250V, I <sub>C</sub> =2.0A,			2.9	μS
t <sub>F</sub>	Fall Time	I <sub>B1</sub> =0.4A, I <sub>B2</sub> =-0.4A, T <sub>P</sub> =30μs		0.2		μS
V <sub>F</sub>	Diode Forward Voltage	I <sub>F</sub> = 2A			2.5	V

### **Typical Performance Characteristics**

Figure 1. Static Characteristic




Figure 2. DC Current Gain




Figure 3. Collector-Emitter Saturation Voltage




Figure 4. Base-Emitter Saturation Voltage




Figure 5. Resistive Load Switching Time





Figure 6. Forward Biased Safe Operating Area



### **Typical Performance Characteristics** (Continued)

Figure 7. Reverse Biased Safe Operating Area





Figure 8. Power Derating Curve





ON Semiconductor and in are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at <a href="www.onsemi.com/site/pdt/Patent-Marking.pdf">www.onsemi.com/site/pdt/Patent-Marking.pdf</a>. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and exp

#### **PUBLICATION ORDERING INFORMATION**

#### LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor 19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada Email: orderlit@onsemi.com N. American Technical Support: 800–282–9855 Toll Free USA/Canada
Europe, Middle East and Africa Technical Support: Phone: 421 33 790 2910
Japan Customer Focus Center
Phone: 81–3–5817–1050

ON Semiconductor Website: www.onsemi.com

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative